
Detecting the distance to an object with an ultransonic sensor

With the capture capability of Netzer a simple ultrasonic sensor like the HC-SR04 module can be used.






For that reason the sensor shall be connected like:

Sensor signal	Netzer signal	Further descriptions
VCC	-	Connect the sensor to +5V
GND	GND	Ground signal
TRIG (I)	IO3	The trigger signal
ECHO (O)	IO0, SPI_INT	The echo signal. Due to the Netzer pins are +5V tolerant, no voltage divider is needed!

IO3

IO3 is used for generating the trigger signal. Datasheet of the sensor stats that at least 10 µs pulse must be generated to start the measurement.



The image shows how to configure IO3.


Depending on the configured unit the following value must be written to IO3 to get the 10 µs impulse:

Unit	**Value**
100ns	100 (0x64)
200ns	50 (0x32)
400ns	25 (0x19)
800ns	13 (0x0D)

The easiest way is to configure the impulse as startup value like shown in image above.

IO0


IO0 is triggered by the rising edge of the sensor capture signal ECHO.



Important is to mark the “Impulse timer Reset” checkbox. Configured like this the rising edge of the ECHO signal will start the capture timer.

SPI_INT

SPI_INT is connected to the ECHO pin, too.



The falling edge of the ECHO signal will stop the capture timer and finally show the result on the GPIO webpage.

Result

Depending on set time resolution the measured value must be multiplied with the appropriate unit.

If the result is *0x1234* at resolution *800ns* the measured pulse width is *3.728 ms*.

The velocity of sound in dry air is 343 m/s (at 20°C) or *34.3 cm / ms*.

3.728 ms x 34.3 cm / ms = *127.87 cm* is the propagation the signal takes. Due to the echo that two ways are measured so the result must be divided in halves: *63.94 cm*

From:
http://www.mobacon.de/dokuwiki/ - **MoBaCon**

Permanent link:
http://www.mobacon.de/dokuwiki/doku.php?id=en:netzer:hc-sr04&rev=1412348113

Last update: **2025/06/11 20:42**