


# Detecting the distance to an object with an ultrasonic sensor

With the capture capability of Netzer a simple ultrasonic sensor like the HC-SR04 module can be used.



For that reason the sensor shall be connected like:

Sensor signal	Netzer signal	Further descriptions
VCC	-	Connect the sensor to +5V
GND	GND	Ground signal
TRIG (I)	IO3	The trigger signal
ECHO (O)	IO0, SPI_INT	The echo signal. Due to the Netzer pins are +5V tolerant, no voltage divider is needed!

## IO3

IO3 is used for generating the trigger signal. Datasheet of the sensor stats that at least 10  $\mu$ s pulse must be generated to start the measurement.

### IO3 (ID d)

Digital input  
Alert events:

Digital output  
Startup value:  0  1

PWM output  
Frequency \*:  Hz  
Logic:  0  1  
Startup value:

Impulse output  
Logic:  0  1  
Startup value:

Input capture  
Capture:  On falling edges  On rising edges

Mode \*:   
Unit \*:  ns

\* Parameter for IO3 and SPI\_INT

The image shows how to configure IO3.

Depending on the configured unit the following value must be written to IO3 to get the 10 µs impulse:

Unit	Value
100ns	100 (0x64)
200ns	50 (0x32)
400ns	25 (0x19)
800ns	13 (0x0D)

The easiest way is to configure the impulse as startup value like shown in image above.

## IO0

IO0 is triggered by the rising edge of the sensor capture signal ECHO.

### IO0 (ID a)

Digital input

Alert events:

---

Digital output

Startup value:  0  1

---

Edge trigger:

Impulse timer:  Reset

Edge filter:

Edge counter:

Edge counter value: 0  Reset

Important is to mark the "Impulse timer Reset" checkbox. Configured like this the rising edge of the ECHO signal will start the capture timer.

## SPI\_INT

SPI\_INT is connected to the ECHO pin, too.

## SPI\_INT (ID j)

Digital input  
Alert events:

Digital output  
Startup value:  0  1

PWM output  
Frequency \*:  Hz  
Logic:  0  1  
Startup value:

Impulse output  
Logic:  0  1  
Startup value:

Input capture  
Capture:  On falling edges  
 On rising edges

Mode \*:   
Unit \*:  ns

\* Parameter for IO3 and SPI\_INT

The falling edge of the ECHO signal will stop the capture timer and finally show the result on the GPIO webpage.

## Result

Depending on set time resolution the measured value must be multiplied with the appropriate unit.

The velocity of sound in dry air is 343 m/s (at 20°C).

From:  
<https://www.mobacon.de/dokuwiki/> - MoBaCon

Permanent link:  
<https://www.mobacon.de/dokuwiki/doku.php?id=en:netzer:hc-sr04&rev=1412344553>

Last update: 2025/06/11 20:42

